

DWC-B7753TIR: Star-Light AHD™ 2.1MP/1080p bullet camera with 3.6mm fixed lens



WHAT'S IN THE BOX					
Star Wrench (T-20)		1	Screws and Plastic Anchors (4pcs)	iiii 4444	1 Set
Mounting Template Sheet	,	1	Quick Setup and Installation Guide		1 Set
DC plug cable		1			

NOTE: Download all your support materials and tools in one place

- 1. Go to: http://www.digital-watchdog.com/resources
- 2. Search your product by entering the part number in the 'Search by Product' search bar. Results for applicable part numbers will populate automatically based on the part number you enter.
- 3. Click 'Search'. All supported materials, including manuals and quick start guide (QSGs) will appear in the results.



Attention: This document is intended to serve as a quick reference for the initial setup. It is recommended that the user read the entire instruction manual for complete and proper installation and usage.



## STEP 1 - PREPARING TO MOUNT THE CAMERA

- 1. The mounting surface must withstand five times the weight of your camera.
- 2. Do not let the cables get caught in improper places or the electric line cover can be damaged. This may cause a short or fire.
- 3. Using the mounting template sheet or the camera itself, mark and drill the necessary holes in the wall or ceiling.

## STEP 2 - CABLING THE CAMERA TO **EXTERNAL DEVICES**

Pass the wires through the mount bracket and make all necessary connections. Connect the BNC cable and power cables to the camera.

## STEP 3 - INSTALLING THE CAMERA

- 1. Once all cables have been connected, use the screws included with the camera to properly mount and secure the camera to the mounting surface.
- 2. To adjust the camera's tilt, loosen the screws at the base of the camera's bracket. The camera's max angles are:
  - Pan: 0°~ 360°
  - Tilt: 0°~ 90°

NOTE: This camera does not have local OSD controls. Use the UTC function to control the camera's OSD settings from a UTC-enabled recorder, such as the VMAX® A1 Plus™.

